ISSN: 2664-9640

A Survey on Analog-Domain Reconfigurable Active Filters: Progress over the Past Decade

Shining Wang[a]

School of Equipment Engineering, Shenyang Ligong University, Shenyang 110159, China

[a]wsn050918@163.com

Abstract

Modern electronic systems have growing demands for real-time reconfigurable signal-processing functions, which makes analog active filters an essential underlying technology. This paper summarizes research advances published from 2014 to 2024. Three mainstream circuit topologies are analyzed in detail: designs built around operational transconductance amplifiers (OTAs), second-generation current-controlled conveyors (CCCIIs), and voltage-controlled current sources (VCCSs). The practical connotation of reconfigurability is clarified, covering cutoff-frequency tuning, quality-factor modification, and filter-mode transition. Additional discussion is conducted on circuit-level implementations such as digitally-controlled analog filters, switched-capacitor circuits, and programmable analog arrays.Published literature demonstrates remarkable performance gains regarding bandwidth, power efficiency, linearity and noise specifications, with expanding deployment in 5G/6G communications, automotive-electronics and IoT applications. Even with such progress, multiple long-standing technical bottlenecks still exist. Trade-offs between reconfiguration speed and tuning accuracy, together with parasitic effects and process deviations, create strict performance limitations. For future research directions, potential technical breakthroughs may stem from AI-assisted design pipelines, integration of novel devices, and thorough system-level co-optimization.

Keywords

Reconfigurable Filter; Active Filter; Analog Signal Processing; Frequency Tuning.

1. Introduction

Reconfigurable active analog filters act as essential building units for contemporary signal-processing systems, with remarkable advances accumulated throughout the past decade. Driven by fast-growing 5G communications, Internet of Things (IoT), and biomedical electronics sectors, the worldwide analog IC market grew from 54.7 billion USD in 2019 to 73.2 billion USD in 2023[1], with reconfigurable analog components claiming a large portion of this market. Classic fixed-parameter filters are incapable of fulfilling dynamic performance specifications demanded by multi-standard, multi-mode communication systems. On the contrary, reconfigurable active filters support dynamic modification of filtering responses to fit diverse use cases including software-defined radio, adaptive signal processing, and intelligent sensor interfaces. State-of-the-art CMOS-based realizations drive integration density and power efficiency to improved levels, alongside enhanced reconfiguration precision and transient response. Such advantageous features bring practical commercial returns for physical products.

ISSN: 2664-9640

2. Fundamentals and Classification of Analog-Domain Reconfigurable Active Filters

2.1. Fundamentals and Classification of Analog-Domain Reconfigurable Active Filters

Reconfigurable active filters work through real-time modification of key transfer-function parameters. Circuit designers frequently employ voltage-controlled oscillators (VCOs), current-bias trimming, or transconductance modulation to realize such functions[2]. Voltage-mode tuning alters the bias voltage across active devices so as to vary transconductance, enabling continuous tuning for frequency and quality-factor metrics. This method offers comparatively simple hardware realization and rapid transient behavior, though it is vulnerable to supply-rail noise and temperature drifts. For another option, current-tuning approaches utilize variable current sources to adjust the bias current of operational transconductance amplifiers (OTAs). This enables more delicate parameter handling and makes these circuits favorable for low-power use cases. In contrast, transconductance-oriented tuning realizes discrete parameter adjustment using digitally-controlled resistor or capacitor arrays. Even with its limited tuning coverage, this method provides superior long-term stability and reproducibility[3].

The filter transfer function can be expressed in terms of transconductance and capacitance. For a second-order low-pass filter:

$$H(s) = \frac{G_{m1}G_{m2}}{C_1C_2s^2 + G_{m3}C_2s + G_{m1}G_{m2}}$$

where the cutoff frequency and quality factor depend on the transconductance parameters G_{m1}, G_{m2}, G_{m3} and capacitances C_1, C_2 Varying these parameters yields different filtering characteristics.

2.2. Physical Realization Schemes for Reconfiguration Mechanisms: Voltage Control, Current Tuning, and Transconductance Adjustment

Analog reconfigurable filter architectures have continuously advanced over the past decade, evolving from conventional Gm-C (transconductance-capacitor) structures toward active-RC and hybrid circuit configurations[4]. Though early-stage GmC filters exhibit decent frequency tuning capacity, transconductance nonlinearity and parasitic impacts create severe performance bottlenecks at high-frequency operation. Adopting high-precision operational amplifiers combined with resistor networks, active-RC topologies achieve obvious enhancements on linearity and noise specifications, yet they come with higher power dissipation and reduced tuning scope. Hybrid architectures combine the wide tuning capacity of GmC circuits and the high precision offered by active-RC structures. Multi-stage cascading and adaptive biasing techniques are adopted to achieve considerable comprehensive performance promotion. Cutting-edge hybrid designs further embed digital calibration loops for real-time compensation of process variations and temperature drift.

The transfer function of a hybrid architecture is more complex, as it must account for contributions from multiple signal paths:

$$H_{hybrid}(s) = \frac{A_1H_{GmC}(s) + A_2H_{RC}(s)}{1 + \beta(s)[A_1H_{GmC}(s) + A_2H_{RC}(s)]}$$

ISSN: 2664-9640

where A_1 and A_2 are weighting factors, and β(s) is the feedback network transfer function. Optimal frequency response and system stability can be achieved by appropriately tuning these parameters[5].

3. Key Performance Metrics and Design Challenges

3.1. Trade-offs Among Tuning Range, Linearity, and Power Consumption

One major bottleneck for contemporary reconfigurable active filter design is to attain wide frequency tuning span, favorable linearity and low-power operation concurrently. A wide tuning coverage demands a large variation range for transconductance. Such substantial parameter offset alters the bias operating points of active devices and further deteriorates linear-range performance. Recent published studies indicate that total harmonic distortion (THD) is capable of falling below −60 dB under a 10:1 frequency tuning ratio.[6]. The coupling relationship between power cost and circuit performance proves to be much more complicated. High-performance reconfigurable filters usually require numerous parallel signal paths and sophisticated control circuitry, giving rise to prominent static power consumption. Dynamic power-management strategies are able to reduce average power dissipation by 30–50 %.[7]. Predistortion compensation and multi-path cancellation act as primary techniques to enhance linearity. Even so, such approaches bring extra costs, including extra hardware circuits and higher calibration complexity.

A fundamental physical limitation lies between the quality factor and power consumption of the system:

$$P_{min} = \frac{4\pi k_B T \cdot BW \cdot Q^2}{SNR_{min}}$$

where k_B represents Boltzmann's constant, T denotes absolute temperature,BW stands for bandwidth, Q is the quality factor, and SNR_{min} corresponds to the minimum required signal-to-noise ratio. This reveals an inherent trade-off between high-Q performance and low power dissipation, which has to be considered in system-level design.

3.2. Effects of Process Deviations, Temperature Drift, and Long-Term Reliability upon Reconfiguration Precision

Process dispersions and environmental disturbances constitute major factors that deteriorate the precision and reliability of reconfigurable filters. As CMOS process nodes keep shrinking, random and systematic parameter spreads of semiconductor devices become more pronounced. Statistical test results show that under 40 nm CMOS technology, the 3σ deviation of transconductance parameters reaches ±15 %, whilst capacitor matching precision stands at approximately ±2 %.These mismatches exert substantial influences on the filter's center-frequency and quality-factor precision[8]. Temperature-caused drift poses another complicated technical challenge. In general, transconductance has a negative temperature coefficient, while resistors show positive temperature-relevant characteristics. Joint action of these two effects produces noticeable performance variations for filters over the industrial temperature span of −40 °C to +85 °C. Long-term circuit stability is primarily governed by electromigration, hot-carrier effects, and stress-induced migration. After devices work under high-temperature conditions for 1000 hours, key parameters may drift by 5–8 %. To mitigate such undesirable influences, real-time calibration and temperature-compensation schemes are widely employed in contemporary circuit implementations. By means of on-die temperature sensors paired with adaptive algorithms, temperature-originated drift can be constrained within ±1 %.

ISSN: 2664-9640

The temperature compensation model is expressed as:

$$f_c(T) = f_0 \cdot [1 + \alpha_1(T - T_0) + \alpha_2(T - T_0)^2] \cdot [1 + \beta \cdot V_{comp}(T)]$$

where f_0 is the center frequency at reference temperature T_0, α_1 and α_2 are first- and second-order temperature coefficients, and $V_{comp}(T)$ is the temperature compensation voltage. Tuning these parameters greatly enhances temperature stability.

4. Typical Technological Advances and Application Cases in the Last Decade

4.1. Broadband Low-Noise Reconfigurable Baseband Filters for 5G/6G Communication Systems

Targeting 5G/6G communication infrastructures, broadband low-noise reconfigurable baseband filter techniques have achieved notable advances throughout the past decade, yielding great improvements in frequency coverage and noise performance[9]. Baseband filters deployed within 5G systems are required to handle bandwidth requirements ranging from tens of megahertz into the gigahertz domain, and deliver multi-band capability spanning 600 MHz to 71 GHz[10].Nowadays, reconfigurable filters built around folded-cascode operational transconductance amplifiers (FC-OTAs) represent one prevailing mainstream solution. Negative-feedback compensation and multi-stage cascaded topologies are incorporated within these circuits to achieve wide-bandwidth operation at low power dissipation. Implemented in advanced process nodes, a 28 nm CMOS reconfigurable baseband filter operates with a 1.2 V supply rail. It achieves a 2 GHz tuning range and maintains pass-band ripple below 3 dB.

$$H(s) = \frac{K \cdot \omega_0^2}{s^2 + \frac{\omega_0}{Q}s + \omega_0^2}$$

For the given formula, $H(s)$ stands for the filter transfer function, K refers to the gain factor, ω_0 denotes the center frequency, and Q corresponds to the quality factor. A digital control module carries out real-time adjustment of the transconductance parameter g_m for center-frequency tuning.Various novel techniques are adopted for improving noise performance, including differential signal-processing architectures, adaptive biasing circuits, and on-chip calibration units. The differential structure achieves effective suppression for common-mode and supply-rail noise, producing input-referred noise density below 2.2 nV/$\sqrt{\text{Hz}}$[11]. Adaptive biasing circuitry dynamically modifies the bias operating points of each amplifier stage in response to process-corner variations, maintaining an optimal signal-to-noise ratio over various environmental conditions.

4.2. High-Robustness Integrated Realizations for Automotive-Grade and Industrial IoT Applications

Automotive-grade use cases place very stringent reliability requirements upon analog-domain reconfigurable active filters. Such devices shall operate over the temperature span of −40 °C to +125 °C, endure vibration acceleration higher than 20 g, and sustain steady performance throughout a 15-year service cycle. Fueled by fast market expansion, the automotive-electronics market has expanded from 218 billion USD in 2019 to 342 billion USD in 2024, with sensor signal-conditioning circuits accounting for a substantial market fraction[12]. Reconfigurable filters adopting differential OTA (operational transconductance amplifier)

ISSN: 2664-9640

architectures fit such harsh operating conditions, delivering favorable thermal properties alongside strong interference rejection. Fundamentally, transconductance tuning is applied to compensate frequency deviations caused by temperature fluctuations.

$$G_m(T) = G_{m0} \cdot [1 + \alpha(T - T_0)] \cdot K_{comp}(T)$$

where $G_m(T)$ stands for temperature-dependent transconductance, α is the temperature coefficient, and $K_{comp}(T)$ denotes the temperature compensation factor. Comparably, the Industrial Internet of Things (IIoT)puts forward various demand for reconfigurable filters[13].Driven by smart manufacturing and Industry 4.0 deployment, industrial sensor nodes increase exponentially and exceeded 11 billion worldwide in 2024[14].

Based on advanced system-on-chip (SoC) design guidelines, high-reliability integrated implementations merge digital control logic, analog signal-processing blocks, and power-management units inside one single die. These architectures greatly improve circuit reliability and cut down total system costs simultaneously.Such integrated hardware commonly employs redundant topologies alongside adaptive calibration functions. It enables real-time monitoring and tuning for filter-relevant parameters, so that target performance specifications can be preserved even under harsh operating conditions[15].

5. Conclusion

From 2014 to 2024, reconfigurable active filter approaches for the analog domain have seen remarkable progress and extensive practical adoption. In terms of hardware implementation, reconfigurable topologies constructed around OTAs, CCCIIs and VCCSs have attained considerable maturity. Likewise, digitally-controlled analog filters alongside switched-capacitor filter implementations yield prominent advances in frequency tuning coverage, reconfiguration accuracy and power dissipation handling.

For core performance benchmarks, state-of-the-art reconfigurable active filters show qualitative enhancement versus their counterparts from ten years ago, most notably in bandwidth broadening, linearity optimization and noise reduction. Frequency tuning can cover multiple orders of magnitude in typical cases; the adjustable quality-factor window is considerably enlarged, and filter-mode reconfiguration gains much greater flexibility.

Diversified application scenarios have greatly propelled such technical evolution. Apart from conventional software-defined radio, practical uses now cover biomedical signal processing, IoT sensor interfaces and multi-standard communication systems. Besides, rising market requirements for product diversity keep pushing forward technical innovations in this field.

Notwithstanding these notable accomplishments, present-day techniques are still confronted with practical hurdles. Key concerns cover the speed-accuracy trade-off during reconfiguration, mitigation of parasitic influences, and compensation against process deviations. Upcoming research directions focus on AI-driven design optimization, deployment of innovative semiconductor components, together with system-oriented co-design strategies. These technical progresses are projected to expand application scopes within 5G/6G communications, edge computing and intelligent sensing scenarios. As manufacturing procedures and design methodologies keep advancing, reconfigurable active filters operating in the analog domain are set to witness further technical progress and expanded application opportunities over the next ten-year period.

ISSN: 2664-9640

References

[1] World Semiconductor Trade Statistics. (2024). *Semiconductor market statistics and forecasts*. https://www.wsts.org

[2] Zhao, H. (2025). *Design of a low-noise second-order Sallen-Key low-pass filter with switched capacitors* [Unpublished master's thesis]. North China University of Technology.

[3] Li, Q. H., Tian, Y. Y., & Wu, Y. X. (2026). Low-band wireless spectrum sensing and resource allocation in 5G communication networks from an internet perspective. *China Broadband*, *22*(04), 22–24.

[4] Zhang, X. W., Min, F. H., Cao, Y., & Ye, B. M. (2024). Study on oscillation behavior of Sallen-Key low-pass filter circuits based on hybrid diodes. *Journal of Nanjing Normal University (Engineering and Technology Edition)*, *24*(2), 1–10.

[5] Wang, Z. (2024). *Design of a wideband active low-pass filter for 5G RF receivers* [Unpublished master's thesis]. Southeast University.

[6] Yi, W., Wang, B., Wu, X. B., & Zhang, D. Z. (2024). *Radar receiver technology*. Publishing House of Electronics Industry.

[7] Wang, Z. (2024). *Design of a wideband active low-pass filter for 5G RF receivers* [Unpublished master's thesis]. Southeast University.

[8] Lan, H. K. (2023). *Research on key technologies of reconfigurable RF integrated circuits* [Unpublished master's thesis]. Xidian University.

[9] Liu, Y., Wei, X. H., Xie, X., Zhang, Y. Y., Wang, M., & Hong, X. (2023). Multi-parameter simulation analysis method for Sallen-Key filters. *Laboratory Research and Exploration*, *42*(5), 117–121.

[10] Li, Q. H., Tian, Y. Y., & Wu, Y. X. (2026). Low-band wireless spectrum sensing and resource allocation in 5G communication networks from an internet perspective. *China Broadband*, *22*(04), 22–24.

[11] Yu, J. W., & Diao, S. X. (2022). Design of a reconfigurable active filter IC. *Journal of East China Normal University (Natural Science)*, (2), 143–154.

[12] Yu, J. W., & Diao, S. X. (2022). Design of a reconfigurable active filter IC. *Journal of East China Normal University (Natural Science)*, (2), 148–159.

[13] Zhang, L., et al. (2023). A novel Nauta transconductor for ultra-wideband gm-C filter with temperature calibration. In *Proc. IEEE International Symposium on Circuits and Systems (ISCAS)* (pp. 1–5).

[14] Industry Research. (2026, April). *Wireless sensors market size, share, growth, and industry analysis, 2024*. shturl.cc/4nVYWVUdacUytJM3jfSxeMKcqugoOnWoGWTeThqVJyMmxPYqWmmarcxFVbETID0QjoAqx1HzCCnhN7mJ7UUI3KZ1IMkeNyfRcNU8JQY98ko4dlXf5LH3djHZ2BqcqJQ

[15] Zhou, Y. L., Chen, C. M., Liu, X. D., & Zhang, Y. Y. (2025). A triple-mode reconfigurable filter. *Journal of Chengdu University of Information Technology*, (3), 65–68.